


MODELS 9S204-9S232-9S242-9S244-9S262-9S263-9S264

CHASSIS No. 5905

SOCKET VOLTAGES

Tube	Position	1	2	3	4	5	6	7	8	9
6K7	R. F.	0	0	240	80	0	—	6.2	0	—2
6L7	Converter	0	6.2	240	80	—7	—	0	0	—1
6J5	Osc.	0	6.2	130	—	—8	—	0	0	—
6K7	I.F.	0	6.2	237	80	0	—	0	0	—1
6H6	2nd Det. A.V.C.	0	0	—2.5	—2	—2.5	—	6.2	—2	—
6F5	1st Audio	0	0	—	82	—	—	6.2	—2	—2.5
6F6	Power	0	0	225	240	—3.5	—	6.2	—4.5	—
5Y4	Rect.	0	—	AC	—	AC	—	298	298	—
		H	Ep	Eg	Et	Ek	H			
6T5	Target	0	10	—2	240	—2	6.2			



**BOTTOM VIEW
OF SOCKET**

All voltages measured from point indicated to ground using a 1000 Ohm per Volt meter, antenna and ground disconnected. Line voltage 117V. Consumption 75W. Power output 4.5W.

ALIGNMENT PROCEDURE

Operation	Connect Test Oscillator to—	Dummy Antenna	Set Test Osc. to	Band	Set Dial At	Adjust Trimmers	Purpose
1	1st Det. Grid	1/2 Mfd.	456	Br'dc't	600	ABCD	I. F. Alignment
2	Rec. Ant. Post	200 Mmfd.	1500	"	1500	F	Set Osc. to Scale
3	" " "	200 Mmfd.	1500	"	1500	GH	Algnt. of Ant. & Det
4	" " "	200 Mmfd.	600	"		J	Rock gang & adj. for max. output
5				"		FGH	Repeat 2 & 3
6	Rec. Ant. Post	400 Ohms	18000	S.W.	18000	K	Set Osc. to Scale
7	" " "	400 Ohms	16500	S.W.	16500	LM	Rock gang & adj. for max. output
8	" " "	400 Ohms	5500	Police	5500	N	Rock gang & adj. for max. output

LOCATION OF TRIMMERS

